



# VS-101AV

SWITCHERS, MATRIX  
SWITCHERS &  
CONTROLLERS

## 10X1 COMPOSITE VIDEO & STEREO AUDIO MECHANICAL SWITCHER



### SPECIFICATIONS

INPUTS:	10 video, 1Vpp/75Ω on BNC connectors, 10 audio stereo, + 4dBm typical, on RCA connectors.
OUTPUTS:	1 video, 1Vpp/75Ω on a BNC connector 1 audio stereo, + 4dBm typical, on RCA connectors.
SWITCHING SYSTEM:	Mechanical, "Break-before-make", Audio- Follow-Video mode.
BANDWIDTH (-3DB):	500 MHz (video). 100 kHz (audio).
CROSSPOINTS:	10 for video, 10 x 2 for audio, 1 set active at any given time.
SIGNAL LEVELS:	Up to 3Vpp video, +30dBm audio.
DIMENSIONS(W,D,H):	48.3cm x 10.2cm x 4.4cm, (19" x 4" x 1.7") W, D, H.
WEIGHT:	1.5kg.(3.3lbs) approx.

### DESCRIPTION

The VS-101AV is a high performance switcher for composite video and unbalanced audio signals. It switches any one of 10 composite video and unbalanced stereo audio signals to a single composite output.

- High Bandwidth - 500MHz (-3dB).
- Mechanical (Passive) Switching - No power required.
- Standard 19" Rack Mount Size - 1U.

